



MA-WD56-DP16

4.9-6.1 GHz Dual Polarized Base Station Antenna, 90°

MARS 90° Broadband Dual Polarized Sector Antenna provides a cost effective solution for large scale WLL, WLAN, H-LAN, ISM, UNII, Public Safety, Municipal MESH Networks and Point-to-Multi-Point applications.

Additional Features:

- Stable performance with 16 dBi of gain.
- Compact size allowing easy blending with any environment.
- Tilt mount allowing quick and easy installation.
- UV protected radome suitable for harsh environment installations.



Specifications								
Electrical								
Frequency range	4.9-6.1 GHz							
GAIN, typ.	16 dBi							
VSWR, max.	1.7 : 1							
Polarization	Dual Vertical & Horizontal							
3 dB Beam-Width, H-Plane, typ.	90°							
3 dB Beam-Width, E-Plane, typ.	8°							
V-Pol.	ETSI EN 302 085 V1.2.3 – CS2							
Side Lobes, min.	ETSI EN 302 085 V1.2.3 – CS2 ETSI EN 302 085 V1.2.3 – CS3							
	-15 dB							
Cross Polarization, min.								
Front to Back Ratio, min.	-30 dB							
Port to Port Isolation, typ.	-30 dB							
Input power, max.	10 Watt							
Input Impedance	50 Ohm							
Lightning Protection	DC Grounded							
Mechanical								
Dimensions (HxWxD)	370 x 370 x 40 mm (14.5" x 14.5" x 1.6")							
Weight	2 kg.							
Connector (without enclosure)	2 x N-Type, Female							
Connector (with enclosure)	2 x SMA							
Back Plane	Aluminum protected through chemical passivation							
Radome	UV Protected Polycarbonate							
Enclosure - Large	287 x 287 x 68 mm. (External dimension)							
Mount	See ordering options							
Environmental								
Operating Temperature Range	-55°C to +65°C							
Vibration	According to IEC 60721-3-4							
Wind Load	200 km/h (survival)							
Flammability	UL94							
Water Proofing	IP-67							
Humidity	ETS 300 019-1-4, EN 302 085 (annex A.1.1)							
Salt Fog	According to IEC 68-2-11							
Ice and Snow	25mm radial (survival)							
Ordering Options								
MA-WD56-DP16	Antenna Suited for MNT-22 (optional wall/pole adjustable mount)							
MA-WD56-DP16B	Antenna with MNT-22 (optional wail/pole adjustable mount)							
MA-WD56-DP16SMEL	Antenna with large enclosure, 2xSMA Connectors and MNT-22							
MA-WD56-DP16SMELZ	Antenna with large enclosure, 2xSMA Connectors with PEMs and MNT-22							
Patterns are available on our website								

Patterns are available on our website

MARS Antennas & RF Systems proprietary information

MARS reserves the right to make technical changes or modifications to any of its products and specifications without prior notice and without implementing such changes to prior supplied products. Product images are representative and indicative only. Warranty terms and general conditions of sale are applicable on any purchase of any product, available on MARS website.

3 Hamanor st. Holon 5886103, P.O.Box 1852 Holon 5811801, Israel							
Tel: +972-3-5599661	•	Fax: +972-3-5599677	•	e-mail: mars@marsant.co.il	•	web: www.mars-antennas.com	